

Conventional Smoke Detector SD12

Product Description:

This product is used for detect the Smoke and sending signal to control panel. Photoelectric technology is used in this sensor. The basic principle of detecting carbon particle present in smoke by using Infrared diodes.

When smoke enters the chamber diode receives more light and the detector gives out alarm signal and also turn ON red led for local indication.



Product Features & Specifications:

- Dual fire LED indication.
- LPCB approved.
- Photo-electric technology is used.
- Current output.
- Stylish look.
- Compatible with all fire panel.
- Low standby current.

Technical Specifications

Power Supply	9 to 33VDC	Output	Current Output
Standby Current	20uA	LED Indication	Dual RED Fire LED Indication
Alarm Current	35mA to 83mA	Working Temperature	-10°C to 50°C
Humidity	0% to 95% Rh		

Applications:




Offices



Shops



Factories



Complex